

PUZZI 2/1 BP

Maximum freedom of movement when removing stains down to the fibre on all types of textiles: portable, powerful 36 V cordless spray extraction machine with ergonomic upholstery nozzle.



Made in Europe



Order no. 1.101-750.0

- Ideal for quick and easy stain removal
- Powerful 36 V battery-powered spray extraction machine
- Ergonomically designed and extra-short upholstery nozzle

Technical data

| | | |
|---|-----------------|--|
| EAN code | | 4066529097996 |
| Battery platform | | 36 V battery platform |
| Tank of fresh/dirty water | l | 1.7 / 2.9 |
| Air flow | l/s | 16 |
| Vacuum | kPa | 16 |
| Spray volume | ml/min | 350 |
| Spray pressure | MPa | 0.16 - 0.22 |
| Turbine capacity | W | 350 |
| Pump capacity | W | 4 |
| Rated input power | W | 350 |
| Sound pressure level | dB(A) | 70 |
| Standard accessory ID | | ID 30 |
| Number of batteries required | Piece(s) | 1 |
| Runtime per battery charging | min | Normal mode: 46 (7.5 Ah) / Normal mode: 37 (6.0 Ah) |
| Charging current | A | 6 |
| Power supply for battery charger | V / Hz | 100 - 240 / 50 - 60 |
| Colour | | anthracite |
| Weight without accessories | kg | 3.7 |
| Weight incl. packaging | kg | 5.4 |
| Dimensions (L × W × H) | mm | 410 × 235 × 250 |

Equipment

| | | |
|--|----------|----------------------------------|
| Variant | | Battery and charger not included |
| Spray/suction hose | m | 1.9 |
| Hose transport lock | | ■ |
| Short upholstery nozzle with handle | | ■ |
| Integrated accessory storage | | ■ |
| Fresh water tank | | ■ |
| Dirty water tank | | ■ |
| Detergent | | RM 764 N / 125 ml |
| Nozzle mouthpiece | | Upholstery nozzle / orange |

■ included in the scope of supply.



Outstanding cleaning performance

- Excellent cleaning with a clear 'before-and-after' effect.
- High vacuum for excellent suction power.
- Extremely fine and even spray pattern from the upholstery nozzle.

Compact design with high mobility

- Also ideal for tight spaces or hard-to-reach places.
- Wireless freedom of movement and flexible use.
- Can be stored anywhere thanks to its compact design.

Professional quality: particularly robust and durable

- Efficient turbine with a service life of 1000 hours.
- Very robust and hard-wearing diaphragm pump.
- Compact, extra-short and hard-wearing upholstery nozzle.

ACCESSORIES FOR PUZZI 2/1 BP

1.101-750.0



| | | Order no. | Description | |
|--|----|-------------|--|---|
| SPRAY EXTRACTION MACHINES | | | | |
| Upholstery tools | | | | |
| Short upholstery nozzle, ergonomic, with integrated handle for PuZZi | 1 | 4.130-063.0 | Ideal in confined areas: very short and ergonomic upholstery nozzle with integrated handle (DN 32) made of plastic for deep cleaning with the PuZZi spray extraction cleaner from Kärcher. | ■ |
| Spray/suction hoses | | | | |
| Spray/suction hose for PuZZi, 2/1 Bp, 1.9 metres long | 2 | 2.885-913.0 | Spray/suction hose, 1.9 metres long, for PuZZi 2/1 Bp battery-powered spray extraction cleaners from Kärcher. Only suitable for use with the short, ergonomic Professional PuZZi upholstery nozzle. | ■ |
| BATTERIES | | | | |
| Battery Power 36/25 | 3 | 2.445-030.0 | 36 V / 2.5 Ah Kärcher Battery Power exchangeable battery with innovative Real Time Technology incl. LCD display to indicate battery level. Suitable for use in all devices on the 36 V Kärcher battery platform. | □ |
| Battery Power 36/50 | 4 | 2.445-031.0 | 36 V / 5.0 Ah Battery Power exchangeable battery with innovative Real Time Technology incl. LCD display to show the battery level. Suitable for all devices on the 36 V Kärcher battery platform. | □ |
| BATTERY CHARGERS | | | | |
| Fast Charger Battery Power 36 V | 5 | 2.445-033.0 | With the fast charger, the 36 V/2.5 Ah exchangeable battery can be charged to 80% in just 48 minutes. Also suitable for all other batteries on the 36 V Kärcher battery platform. | □ |
| STARTERKIT BATTERIES AND BATTERY CHARGERS | | | | |
| Starter kit Battery Power 36/25 | 6 | 2.445-064.0 | The Battery Power 36/25 Starter Kit includes a 36 V/2.5 Ah Battery Power exchangeable battery and a 36 V fast charger. For all devices on the 36 V Kärcher battery platform. | □ |
| Starter kit Battery Power 36/50 | 7 | 2.445-065.0 | Battery Power 36/50 Starter Kit incl. 36 V/5.0 Ah Battery Power exchangeable battery and 36 V fast charger. Suitable for use in all devices on the 36 V Kärcher battery platform. | □ |
| BATTERIES | | | | |
| Battery Power+ 36/75 | 8 | 2.445-043.0 | A capacity of 7.5 Ah guarantees long runtimes for the Battery Power+ 36 V lithium-ion battery. Very powerful, with Real Time Technology via LCD display and protection against overcurrent. | □ |
| Battery Power+ 36/60 | 9 | 2.042-022.0 | Extremely powerful Battery Power+ 36 V lithium-ion battery with a capacity of 6.0 Ah for a long runtime. With innovative Real Time Technology via LCD display and voltage monitoring. | □ |
| BATTERY CHARGERS | | | | |
| Universal charger Battery Power+ 18-36 | 10 | 2.445-054.0 | Universal charging unit Battery Power+ with LED operating status indicator for charging all 18 and 36 V Kärcher Battery Power and Kärcher Battery Power+ lithium-ion batteries. Suitable for wall mounting. | □ |
| Fast charger Battery Power+ 36/60 | 11 | 2.445-045.0 | Charge all 36 V Kärcher Battery Power and Kärcher Battery Power+ lithium-ion batteries with max. 6 A charging current: Quick charger with LED operating status indicator. Easy wall mounting. | □ |
| STARTER KIT | | | | |
| Starter kit Battery Power+ 36/75 | 12 | 2.445-070.0 | Starter Kit Battery Power+ 36/75 with 2 36-V/7.5-Ah batteries and 36-V quick charger for our 36 V Kärcher Battery Power and Kärcher Battery Power+ battery platform devices. | □ |
| Starter kit Battery Power+ 36/60 | 13 | 2.445-071.0 | Kärcher Battery Power+ 36/60 Starter Kit for all machines in the Kärcher 36 V Battery Power+ battery platform. Scope of delivery: 2x 36 V/6.0 Ah batteries and the compatible 36 V quick charger. | □ |

■ Included in the scope of supply. □ Available accessories.